



# Compact Colour LED Printer

Compact Design, Expertly Engineered

HL-L3240CDW



PRINT



WIRELESS

Exclusively available from

**Officeworks** 

[www.brother.com.au](http://www.brother.com.au)

## Compact Colour LED Printer

Combining outstanding performance with fast print speeds, minimal maintenance, and long-lasting supplies.

The compact, whisper-quiet HL-L3240CDW has been expertly engineered to feature the latest industry-standard security. Be confident that this colour LED will meet the needs of your home or small office with ease.

### HL-L3240CDW



### Key features:

- Print speeds of up to 26 pages per minute<sup>9</sup>
- Large paper capacity of 250 sheets<sup>6</sup>
- Automatic 2-sided (duplex) printing
- Gigabit ethernet, 2.4GHz/5GHz Wi-Fi and USB 2.0 connectivity
- Print directly from desktop or mobile app
- 256MB internal memory
- Up to 1,000 black and 1,000 colour pages in-box toners<sup>11</sup>
- High-yield replacement toners available, up to 3,000 black and 2,300 colour pages<sup>11</sup>



#### Compact and expertly engineered

Designed by experts, our most compact colour LED printer delivers high-quality outputs every time, allowing you to make the most of your home and small office space. Every component has been optimised to reduce the overall size of the device without compromising on performance. With easy paper access, this device has been developed to meet the needs of the home and small office.



#### Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to protect your data. The HL-L3240CDW a range of robust features including triple-layer security at a device, network and document level which is verified through external security certification. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.



#### Quiet without compromise

With its streamlined design, the HL-L3240CDW is engineered to print quietly while delivering speeds up to 25% faster than the previous generation, so you can print continuously.



#### Designed to go the distance

Built to perform for longer, the HL-L3240CDW has been designed with you in mind. Made from robust and hard-wearing materials and supported by outstanding service as standard, Brother's award-winning reliability allows you to deliver uncompromised performance at all times.



#### Brother at your side support

Wherever you are in Australia, Brother offers [free product support](#) for the lifetime of your product.

General	
Engine	Colour LED
Carton Contents	Printer, Quick Setup Guide, Users Guide, CD-ROM (Windows), Power Cord, CMYK Toner (TN258C/TN258M/TN258Y/TN258BK) Up to 1,000 pages <sup>11</sup> <b>Belt Unit:</b> Up to 60,000 pages (3-page per job) (BU229CL) <b>Waste Toner Box:</b> Up to 50,000 pages (WT229CL) <b>Drum Unit:</b> Up to 20,000 pages (1-page per job) (DR258CL)
Display	
LED Display	Green x1 (Power), Orange x1 (Error), Green x1 (Data), Green x1 (Wi-Fi)
LCD Display	16 characters x 1 line
Control Panel Switches	Go, Cancel, Secure, OK, Back, +, -, Power On/Off, Wi-Fi
Printer	
Standard Memory	256MB
Print Speed <sup>9</sup>	Up to 26 ppm Mono / Up to 26 ppm Colour
2 Sided Print Speed <sup>9</sup>	Up to 10/10ipm or 5/5ppm (Mono/Colour, based on ISO/IEC 24734)
2 Sided Print	Yes (Automatic)
Emulation	PCL6, BR-Script3
Printer Resolution	600 x 600 dpi, 2400 dpi (2400 x 600) quality
First Print Out Time <sup>10</sup>	Less than 13.5 secs Mono/Colour (From Ready mode and standard tray) Less than 30 secs Mono/Colour (From Sleep mode and standard tray)
Warm Up Time	Less than 24 sec from Sleep, Less than 28 sec from Power On
Resident Barcodes	Code39, Interleaved 2 of 5, FIM(US-PostNet), Post Net(US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN(EAN), ISBN(UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI
Resident Fonts	<b>PCL:</b> 73 scalable fonts, 12 bitmap fonts, 16 bar codes <b>PS:</b> 66 scalable fonts
Quiet Mode	A mode to reduce the printing noise by reducing the print speed
Recommended Monthly Print Volume <sup>8</sup>	1,000 to 3,000 pages
Paper Handling <sup>6</sup>	
Standard Paper Capacity	Up to 250 Sheets
Envelopes Input	Up to 1 envelope, output via rear
Output Paper Capacity	Up to 150 Sheets Face Down (80gsm) 1 sheet face-up (straight paper path)
Media Weights Paper Tray	60 - 163 gsm
Media Weights Manual Feed Slot	60 - 163 gsm
Media Weights Duplex	60 - 105 gsm
Media Size Paper Tray	A4, Letter, Legal, Mexican Legal, India Legal, Executive, A5, A5 Long Edge, A6, B5(JIS), B5(SO), B6(JIS), A4 Short(270mm), Folio, 16K(195x270mm)
Media Size Manual Feed Slot	Width 76.2 to 216 mm, Length 116 to 355.6 mm Envelope; COM-10, DL, C5, Monarch
Media Size Duplex	A4
Media Size Scanner Glass	Up to A4/LTR
Media Types Paper Tray	Plain Paper, Thin Paper, Thick Paper, Recycled Paper
Media Types Manual Feed Slot	Plain Paper, Thin Paper, Thick Paper, Recycled Paper, Bond, Label, Envelope, Envelope Thin, Envelope Thick, Glossy Paper
Media Types Duplex	Plain Paper, Thin Paper, Recycled Paper

Software	
Printer OS Compatibility <sup>3</sup>	<b>Windows</b> 11, Windows 10 (32&64bit), Windows Server 2022, Windows Server 2019, Windows Server 2016, Windows Server 2012 R2 (64-bit), Windows Server 2012 (64-bit) <b>macOS</b> 11 - 13 <sup>3</sup> <b>Linux</b> CUPS, LPD/LPRng (x86/x64 environment)
Software Available	<b>Windows:</b> iPrint&Scan <sup>1</sup> , Status Monitor, BRAdmin Light <sup>1</sup> , BRAdmin Professional <sup>1</sup> , Driver Deployment Wizard <sup>1</sup> <b>Mac:</b> iPrint&Scan <sup>1</sup> , Status Monitor
Printer Driver Functions	<b>Windows:</b> Poster, N in 1, Header-Footer, Watermark, Duplex, Secure Print, Toner Save Mode <b>Mac:</b> N in 1, Duplex, Secure Print, Toner Save
N-up Printing <sup>5</sup>	Windows only
Poster Printing <sup>4</sup>	1 in 2x2, 3x3, 4x4, 5x5 (Windows Only)
Header and Footer Printing <sup>4</sup>	Print the time and date or the user ID on the document (Windows Only)
Watermark Printing <sup>4</sup>	Watermark your documents with predefined text or with your own user-defined messages (Windows Only)
Secure Print <sup>5</sup>	Use Secure Print to ensure that confidential or sensitive documents do not print until you enter a password on the machine's control panel. (Windows/Mac)
Mass Deployment Tool <sup>1</sup>	A configuration tool to help you to install and manage multiple USB-connected or network-connected devices without having to install any additional software
Driver Deployment Wizard <sup>1</sup>	A quick & easy way to deploy Brother printer drivers on a networked Windows <sup>®</sup> PC
iPrint&Scan <sup>1</sup>	Windows/Mac (Print Only)
Mobile/Web Printing	
Mobile Connect <sup>1</sup>	Use Brother Mobile Connect to print, scan, and copy, as well as manage your machine and customize its features.
AirPrint	Print most common file types from any Apple AirPrint enabled application
Mopria <sup>1</sup>	Print most common file types from Mopria™ supported Android devices
Google ChromeOS	Print from your Chromebook
Android Print Service Plugin <sup>1</sup>	Print directly from your Android devices (Android 5.0 or later), to your Brother printer through a Wi-Fi or Wired network
Connectivity	
Interface	Hi-Speed USB 2.0, 10Base-T/100Base-TX/1000Base-T Ethernet, 2.4/5Ghz Wi-Fi
USB Interface	Hi-Speed USB 2.0
Wired Interface	10Base-T/100Base-TX/1000Base-T Ethernet
Wireless Interface	2.4GHz IEEE 802.11b/g/n, 5GHz IEEE 802.11a/n
Wi-Fi Direct	IEEE 802.11g/n (Wi-Fi Direct)
Wireless Mode	<b>2.4GHz</b> IEEE 802.11b/g/n (Infrastructure Mode mode), <b>5GHz</b> IEEE 802.11a/n (Infrastructure Mode mode)
Wireless Setup Support Utility	Wi-Fi Protected Setup (WPS)
Network Protocols IPV4	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/Scan), SNTTP Client, Syslog
Network Protocols IPV6	NDP, RA, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTTP Client, Web Services (Print/Scan), Syslog

Network Management Utilities	
Network Management	<b>Windows:</b> BRAdmin Light, Web Base Management, BRAdmin Professional, Network Remote Setup <b>Mac:</b> Web Base Management, Network Remote Setup <b>Linux:</b> Web Base Management
Web Based Management	Web based print management software embedded onto the device
BRAdmin Professional <sup>1</sup>	For LAN / WAN management using Windows® PC
Email Alerts	E-mail Notification and E-mail Reports
Store Print Log to Network <sup>4</sup>	User level usage data recorded to either a text or csv file direct to a network folder
Security	
Wireless Security Protocols	WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE(AES), Wi-Fi Direct supports WPA2-PSK (AES) only
Wireless Certification	Wi-Fi Certification Mark License (WPA3 - Enterprise, Personal), Wi-Fi Protected Setup (WPS) Identifier Mark License, Wi-Fi CERTIFIED Wi-Fi Direct
IPv4-Filter	Restrict which network users can or cannot access the device over the network (IPv4 only)
Secure Function Lock	Version 3, 100 users
Options	
Optional Warranty <sup>14</sup>	1 or 2 or 3 Years On-Site
Consumables	
Consumables <sup>11</sup>	<b>Belt Unit:</b> Up to 60,000 pages (3-page per job) (BU229CL) <b>Waste Toner Box:</b> Up to 50,000 pages (WT229CL) <b>Drum Unit:</b> Up to 20,000 pages (1-page per job) (DR258CL)
Inbox Consumables <sup>11</sup>	<b>CMYK Toner Standard Yield</b> (TN258C/TN258M/TN258Y/TN258BK) Up to 1,000 pages
Standard Yield Toner <sup>11</sup>	<b>CMYK Toner Standard Yield</b> (TN258C/TN258M/TN258Y/TN258BK) Up to 1,000 pages
High Yield Toner <sup>11</sup>	<b>Black Toner High Yield</b> (TN258XLBK) Up to 3,000 pages <b>Colour Toner High Yield</b> (TN258XLC/TN258XLM/TN258XLY) Up to 2,300 pages

Weights & Measurements	
Size	399(W) x 399(D) x 239(H)mm
Weight	11.2 Kg without consumables 15.2 Kg with consumables
Size With Carton	488(W) x 488(D) x 370(H)mm
Weight With Carton	18 Kg with consumables
Environment	
Power Consumption	<b>Peak:</b> Average 960W, <b>Ready:</b> Average 70W, <b>Sleep:</b> 10W, <b>Deep Sleep:</b> 0.4W, <b>Power Off:</b> 0.04W
Sleep Mode	0-50 min
Toner Save	This reduces the toner usage and helps to reduce the total cost of printer ownership
Power Save	This enables the printer to consume less energy when not in use
Temperature	Operating: 10 - 32°C, Storage: 0 - 40°C
Humidity	Operating: 20 - 80%, Storage: 35 - 85%
Others	
Noise Level	<b>Sound Pressure Level:</b> (Printing) Less than 47 dBA, (Ready) InAudible <b>Sound Power Level:</b> (Printing) Less than 6.39 B(A), (Ready) InAudible
TEC Value	0.4 kWh/Week

- Download from Brother Solutions Centre
- Via Airprint or iPrint&Scan
- Windows only
- Windows/Mac
- Capacity calculated with 80g/m<sup>2</sup> paper
- The recommended monthly print volume is to achieve the best possible performance and printer life
- Print speeds based on ISO/IEC 24734 ([www.brother.com/rd/printspeed](http://www.brother.com/rd/printspeed))
- FPOT (First Print Out Time) based on ISO/IEC 17629
- Approx. declared yield value in accordance with ISO/IEC 19798
- Purchase optional onsite warranty required

All specifications correct at time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.



### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

[www.brotherearth.com](http://www.brotherearth.com)

